

# **EUSSO VoIP Gateway Application Code Release Notes**

January/14/2004

**Revision:** Was: 3.28 Is: 3.29

## **New Features:**

1. Allows user to configure if Ethernet MAC address should be encapsulated in the h323Id filed in RRQ packet.

Syntax for CLI command for facilitating this feature is as follows

**set h323 gk\_rrq\_mac [yes | no]**

### **Syntax Description**

**yes**                Encapsulate Ethernet MAC address in RRQ packet  
**no**                Do not encapsulate Ethernet MAC address in RRQ packet

### **Factory default**

no

2. Allows user to configure maximum alerting timeout.

Syntax for CLI command for facilitating this feature is as follows

**set h323 max\_alt\_to seconds**

### **Syntax Description**

*seconds*            Timeout in seconds ranging from 2 to 50.

### **Factory default**

50

3. Supports an additional dynamic DNS server dyndns Gnudip (server name= 2221, vttsys, proeye).

## **Changes:**

1. Keeps a copy of Ethernet MAC address in flash as backup. Ethernet MAC address will be restored when the IMG detects that it is being corrupted during power on reset.

### **Closed PTRs:**

PTR#	Level	Description
N/A	3	Fail terminating calls to FXO port, if port's valid_call_timer is set.
N/A	2	FXO port not able to proceed from connected state to disconnect state if loop current shutdown is the sole disconnect means.